

## WIRING TABLE

WIRE FUNCTION					
SERIES	TYPE	POWER	GROUND	SELECT	PART NUMBERS
<b>2500 SERIES</b> <i>BRISTOL LOW PROFILE</i>	BEACON	RED	WHITE	BROWN	100BC0005, 100BC0006, 100BC0007, 100BC0017
<b>4000 &amp; 4001 SERIES</b> <i>CHARLOTTE HIGH PROFILE</i>	BEACON	RED	WHITE	BROWN	100BC0001, 100BC0002
<b>4000 SERIES</b> <i>CHARLOTTE LOW PROFILE</i>	BEACON	RED	WHITE	BROWN	100BC0003, 100BC0004
<b>2000 SERIES</b> <i>DARLINGTON SLIM</i>	BEACON	RED	BLACK	N/A	100BC0015
<b>2500 SERIES HIGH</b> <i>RICHMOND HIGH PROFILE</i>	BEACON	RED	BLUE	GREEN	100BC0011, 100BC0012
<b>LB1000 SERIES</b> <i>DAYTONA</i>	LIGHT BAR	RED	BLUE	GREEN	100LB0017
<b>LB3000 SERIES</b> <i>FONTANA</i>	LIGHT BAR	RED	BLUE	GREEN	100LB0027, 100LB0028, 100LB0029, 100LB0030
<b>LB5000 SERIES</b> <i>HOMESTEAD</i>	LIGHT BAR	RED	BLACK		100LB0008, 100LB0009, 100LB0010, 100LB0011, 100LB0012, 100LB0037
<b>LB1500 SERIES</b> <i>PHOENIX</i>	LIGHT BAR	RED	BLUE	GREEN	100LB0032, 100LB0034, 100LB0036
<b>LB4000 SERIES</b> <i>POCONO</i>	LIGHT BAR	RED	BLACK	YELLOW	100LB0018, 100LB0019, 100LB0020, 100LB0021, 100LB0022
<b>LB1100 SERIES</b> <i>SONOMA</i>	LIGHT BAR	RED	BLUE	GREEN	100LB0024, 100LB0026
<b>LB1600 SERIES</b> <i>TALLADEGA</i>	LIGHT BAR	RED	BLACK	YELLOW	100LB0014
<b>600 &amp; 601 SERIES OVAL</b> <i>MICHIGAN</i>	WARNING LIGHT	RED	BLACK	WHITE	100WA0001, 110WA0005, 100WA0025
<b>400 SERIES ROUND</b> <i>MICHIGAN</i>	WARNING LIGHT	RED	BLACK	WHITE	100WA0002, 100WA0006

CIGARETTE LIGHTER ADAPTER			
SERIES	TYPE	PART NUMBERS	OPERATING INSTRUCTIONS
<b>2500 SERIES</b> <i>BRISTOL LOW PROFILE</i>	BEACON	100BC0008, 100BC0009, 100BC0010, 100BC0018	Cigarette lighter adapter has two switches: <b>1. POWER ON/OFF 2. SELECT</b>  <b>To power up the product:</b> Plug the adapter into cigarette outlet, switch on the <i>POWER ON/OFF</i> switch (red light illuminates).  <b>To switch flash patterns:</b> Momentarily press the <i>SELECT</i> switch. Repeat for next pattern.  <b>To power down the product:</b> Switch off the <i>POWER ON/OFF</i> switch (red light shuts off).
<b>2500 SERIES HIGH</b> <i>RICHMOND HIGH PROFILE</i>	BEACON	100BC0013, 100BC0014	
<b>LB1000 SERIES</b> <i>DAYTONA</i>	LIGHT BAR	100BC0015, 100BC0016	
<b>LB1500 SERIES</b> <i>PHOENIX</i>	LIGHT BAR	100LB0031, 100LB0033, 100LB0035	
<b>LB1100 SERIES</b> <i>SONOMA</i>	LIGHT BAR	100LB0023, 100LB0025	
<b>LB1600 SERIES</b> <i>TALLADEGA</i>	LIGHT BAR	100LB0013	